

**PRODUCT DESCRIPTION**

The Edifier Prisma Encore is designed to complement modern PC, monitor styles and personal notebooks and is a treat for your eyes and ears. Connect to a host source via the auxiliary input or simply link to your iPod, iPhone or MP3 player for flexible, instant plug and play music. Prisma Encore with wireless remote makes adjusting the volume easy. There is also a button conveniently located on top of the subwoofer for the control of power and volume.

FEATURES

- Bluetooth pairing capability with A2DP & AVRCP profile support
- 2 way satellite speaker with 3inch mid-range unit and Φ 19mm silk dome tweeter
- Subwoofer with UV gloss coating and down-firing 5inch driver
- Touch sensitive controls for volume, playback control for Bluetooth and standby
- Auxiliary input for versatile connectivity
- Professional amplifier system with Digital Signal Processing (DSP) and Dynamic Range Control (DRC)
- Remote control for volume and audio source selection
- Universal 100V-240V power supply

SPECIFICATIONS

Power output	: RMS 12W \times 2 + 40 W (DRC ON)
Signal to noise ratio	: \geq 85dBA
Frequency response	: 60Hz~20KHz (+/-6dB)
Input type	: Bluetooth/AUX
Input sensitivity	: R/L: 500mV \pm 50mV SW: 350mV \pm 50mV
Bass unit	: 5 inch
Mid-range unit	: 3 inch (78mm)
Treble unit	: Φ 19mm silk dome

ORDERING DETAILS

EAN:
6923520264254
6923520264261

Model no.:
E3360BT
E3360BT

Description:
Black 2.1 audio speakers system
White 2.1 audio speakers system